

**SILICON TRANSISTOR
NPN SILICON EPITAXIAL TRANSISTOR
POWER MINI MOLD**

DESCRIPTION

The 2SC3357 is an NPN silicon epitaxial transistor designed for low noise amplifier at VHF, UHF and CATV band. It has large dynamic range and good current characteristic.


FEATURES

- Low Noise and High Gain
 NF = 1.1 dB TYP., Ga = 8.0 dB TYP. @VCE = 10 V,
 IC = 7 mA, f = 1.0 GHz
 NF = 1.8 dB TYP., Ga = 9.0 dB TYP. @VCE = 10 V,
 IC = 40 mA, f = 1.0 GHz
- Large PT in Small Package
 PT : 2 W with 16 cm² × 0.7 mm Ceramic Substrate.

ABSOLUTE MAXIMUM RATINGS (TA = 25 ° C)

Collector to Base Voltage	VCBO	20	V
Collector to Emitter Voltage	VCEO	12	V
Emitter to Base Voltage	VEBO	3.0	V
Collector Current	IC	100	mA
Total Power Dissipation	PT*	1.2	W
Thermal Resistance	Rth(j-a)*	62.5	° C/W
Junction Temperature	Tj	150	° C
Storage Temperature	Tstg	-65 to +150	° C

* mounted on 16 cm² × 0.7 mm Ceramic Substrate



1.Base 2.Collector 3.Emitter
SOT-89 Plastic Package

ELECTRICAL CHARACTERISTICS (TA = 25 ° C)

CHARACTERISTIC	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITIONS
Collector Cutoff Current	I_{CBO}			1.0	μA	$V_{CB} = 10 V, I_E = 0$
Emitter Cutoff Current	I_{EBO}			1.0	μA	$V_{EB} = 1.0 V, I_C = 0$
DC Current Gain	h_{FE}^*	50	120	300		$V_{CE} = 10 V, I_C = 20 mA$
Gain Bandwidth Product	f_T		6.5		GHz	$V_{CE} = 10 V, I_C = 20 mA$
Feed-Back Capacitance	C_{re}^{**}		0.65	1.0	pF	$V_{CB} = 10 V, I_E = 0, f = 1.0 MHz$
Insertion Power Gain	$ S_{21e} ^2$		9		dB	$V_{CE} = 10 V, I_C = 20 mA, f = 1.0 GHz$
Noise Figure	NF		1.1		dB	$V_{CE} = 10 V, I_C = 7 mA, f = 1.0 GHz$
Noise Figure	NF		1.8	3.0	dB	$V_{CE} = 10 V, I_C = 40 mA, f = 1.0 GHz$

* Pulse Measurement $PW \leq 350 \mu s$, Duty Cycle $\leq 2 \%$


** The emitter terminal and the case shall be connected to the guard terminal of the three-terminal capacitance bridge.

 h_{FE} Classification

Class	RH	RF	RE
Marking	RH	RF	RE
h_{FE}	50 to 100	80 to 160	125 to 250

TYPICAL CHARACTERISTICS (TA = 25 °C)

TOTAL POWER DISSIPATION vs.
AMBIENT TEMPERATURE



FEED-BACK CAPACITANCE vs.
COLLECTOR TO BASE VOLTAGE

